

Product overview



Batteries for Trucks, Buses, Construction, Agriculture

StartPRO FG1355



| Part number | FG1355 | Polarity | |
|---------------------|---------------|---|------------------|
| Technology | Flooded | | |
| EAN/GTIN | 3661024045520 | | |
| Voltage | 12 V | | |
| Capacity | 135.0 Ah | $\Theta \bigcirc \bigcirc$ | |
| CCA | 1000 A | Terminal Type | |
| Length | 514 mm | | |
| Width | 175 mm | 17 | |
| Height | 210 mm | | |
| Box size | DB8 | Ø19.5 | Ø179 |
| Polarity | ETN 3 | | |
| Terminal Type | EN taper post | | |
| Hold Down | B3 | | |
| Weights (subject of | 36.00 kg | PositiveTerminal | NegativeTerminal |
| variation) | | Hold Down | |
| | | 3 notches | 3 notches |
| | | | |

Design, features and specifications are subject to change without notice. We disclaim any representation or warranty, express or implied, concerning the data or recommendations, and in no event shall be liable for any loss or damage claimed to have arisen as a result. Some products may not be available in your local market.